

EZ3+ Outdoor High Power Access Point

Quick Installation Guide

Unpacking Information

Thank you for purchasing the EZ3+ Outdoor High Power AP. Before you start please verify if your package contains the following items:

1. **One Wireless AP**
2. **One Power Adapter**
3. **One PoE Injector**
4. **One Quick Installation Guide**

Installing and Using the EZ3+ High Power AP

Connect the power adapter with the connector end to the power socket in the rear panel of the PoE Injector marked as “power in” and the plug end to an appropriate outlet.

- Connect the “Data IN” port of the PoE Injector with an RJ-45 cable to:
 1. a broad band router to allow wireless clients to connect to WAN, or
 2. a switch to allow wireless clients to communicate with wired LAN, or
 3. a computer directly to configure this AP.
- Connect the “Data OUT” port of the PoE Injector with an RJ-45 cable to the EZ3+ High Power AP RJ-45 port

NOTE: You have to configure the network settings of this AP to be communicable with your router, switch or computer first. To change the default network settings of the AP, please refer to “**PC Configuration**” in user’s manual.

- Connect to the EZ3+ AP wirelessly:

You can communicate with this AP wirelessly after connecting this AP to your LAN. The default SSID of this AP is **E-ZY.NET_EZ3**. To change the SSID or secure your wireless network with encryption, please refer to the user’s manual.

To configure the EZ3+ High Power AP

Before using the EZ3+ AP, you have to configure it through your computer from a WEB browser.


Please follow the steps listed below:

1. Double click the Internet WEB browser icon on your desktop screen (Internet Explorer or Mozilla Firefox.)
2. Type 192.168.1.1 into the URL and press enter

NOTE:

- a. The IP address of your computer should be within the same range with the IP address of the EZ3+ High Power AP.
- b. The default network settings of this AP:

IP address: 192.168.1.1
Subnet Mask: 255.255.255.0
DHCP Server: disabled



After the typing of IP, the status page shows up as the home page of Graphic User Interface. You may click on each folder on left column of each page to get access to each configuration page. Please refer to the user’s manual for configuration details.



You can download the Discovery tool, updated Manual and latest firmware from the product support page :

<http://www.e-zy.net/support>